

U72 Option Switch Settings (Pulse/MDB/RS232 104U)

Supported bill COP 1000, 2000, 5000, 10000, 20000, 50000 6 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject COP 1000 & 2000	ON											
★ Accept COP 1000 & 2000	OFF											
★ Reject COP 5000 & 10000		ON										
★ Accept COP 5000 & 10000		OFF										
★ Reject COP 20000 & 50000			ON									
★ Accept COP 20000 & 50000			OFF									
★ High Acceptance				ON								
★ High Security				OFF								
★ Enable, if fishing, BA doesn't work anymore					ON							
★ Disable, if fishing, BA Stop 3 minute.					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active HIGH								ON				
★ Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject									OFF			
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 COP6(Pulse/MDB/RS232 104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / COP 1000			OFF	OFF
	2 pulse / COP 1000			OFF	ON
	4 pulse / COP 1000			ON	OFF
	20 pulse / COP 1000			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface Bill value	Pulse	MDB	RS232 104U
BV1	COP 1000	COP 1000	COP 1000
BV2	COP 2000	COP 2000	COP 2000
BV3	COP 5000	COP 5000	COP 5000
BV4	COP 10000	COP 10000	COP 10000
BV5	COP 20000	COP 20000	COP 20000
BV6	COP 50000	COP 50000	COP 50000