U72 Option Switch Settings (Pulse/MDB/RS232 104U)

Supported bill INR 5, 10, 20, 50, 100, 500, 2000 7 Bills.

							-		סוווט				
FUNCTIO	ON	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject IN	R 5	ON											
Accept IN	R 5	OFF											
Reject INF	R 10		ON										
Accept INI	R 10		OFF										
Reject INF	R 20			ON									
Accept INI	R 20			OFF									
Reject INF	R 50				ON								
Accept INI	R 50				OFF								
Reject INR	100					ON							
Accept INR	R 100					OFF							
Reject INR	500						ON						
Accept INR	R 500						OFF						
Reject INR	2000							ON					
Accept INR	2000							OFF					
Inhibit Active	HIGH								ON				
Inhibit Active	e LOW								OFF				
Power On St	tacker									ON			
Power On R	Reject									OFF			
Slow Output Pulsa	Lo 50 ms										ON		
Slow Output I tilse	Hi 300 ms										OIN		
Fact Output Pulce	Lo 50 ms										OEE		
Tast Output I uisc	Hi 100 ms										Ort		
Reserved									ON				
★ Reserved		OF							OFF				
Reserved													ON
Reserve	d												OFF
	Reject IN Accept INI Reject INI Reject INI Reject INI Reject INI Accept INI Reject INI R	Accept INR 10 Reject INR 20 Accept INR 50 Reject INR 50 Accept INR 100 Accept INR 100 Accept INR 500 Accept INR 500 Accept INR 500 Accept INR 500 Accept INR 2000 Accept INR 2000 Accept INR 2000 Inhibit Active HIGH Inhibit Active LOW Power On Stacker Power On Reject Slow Output Pulse Fast Output Pulse Tast Output Pulse Reserved Reserved Reserved	Reject INR 5 OFF Accept INR 10 Accept INR 10 Reject INR 20 Accept INR 50 Reject INR 50 Accept INR 50 Accept INR 50 Reject INR 50 Accept INR 50 Reject INR 500 Accept INR 500 Accept INR 500 Accept INR 2000 Accept INR 2000 Accept INR 2000 Inhibit Active HIGH Inhibit Active LOW Power On Stacker Power On Reject Slow Output Pulse Fast Output Pulse Reserved Reserved Reserved Reserved Reserved	Reject INR 5	Reject INR 5	Reject INR 5							

★Manufacture setting

Note: Please reset the bill acceptor after any changes on Dip switch.

U72 INR7(Pulse/MDB/RS232 104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
\star	Reserved	ON			
	Reserved	OFF			
\star	Pulse Mode		ON		
	Other Mode		OFF		
\star	1 pulse / INR 5			OFF	OFF
	2 pulse / INR 5			OFF	ON
	4 pulse / INR 5			ON	OFF
	20 pulse / INR 5			ON	ON

[★]Manufacture setting

DIP SWITCHES SETTING : 2(RS232 104U)

	FUNCTION	SW1	SW2	SW3	SW4
\star	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
\star	Other Mode		OFF		
	MDB			OFF	OFF
\star	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved		·	ON	ON

[★]Manufacture setting

DIP SWITCHES SETTING: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
\star	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
\star	Other Mode		OFF		
*	MDB			OFF	OFF
	RS232 104U		·	OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

[★]Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2)Please open the panel of front, and can see the DIP switch.

Currency Assign Data

	<u> </u>	<u> </u>	
Interface Bill value	Pulse	MDB	RS232 104U
BV1	INR 5	INR 5	INR 5
BV2	INR 10	INR 10	INR 10
BV3	INR 20	INR 20	INR 20
BV4	INR 50	INR 50	INR 50
BV5	INR 100	INR 100	INR 100
BV6	INR 500	INR 500	INR 500
BV7	INR 2000	INR 2000	INR 2000