

U72 Option Switch Settings (Pulse/MDB/RS232 106U)

Supported bill AUD 5, 10, 20, 50, 100 5 Bills.

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|----------------------------------------------------|-----------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject AUD 5 | ON | | | | | | | | | | | |
| ★ Accept AUD 5 | OFF | | | | | | | | | | | |
| ★ Reject AUD 10 & 20 | | ON | | | | | | | | | | |
| ★ Accept AUD 10 & 20 | | OFF | | | | | | | | | | |
| ★ Reject AUD 50 & 100 | | | ON | | | | | | | | | |
| ★ Accept AUD 50 & 100 | | | OFF | | | | | | | | | |
| ★ High Acceptance | | | | ON | | | | | | | | |
| ★ High Security | | | | OFF | | | | | | | | |
| ★ Enable, if fishing, BA doesn't work anymore | | | | | ON | | | | | | | |
| ★ Disable, BA works normally | | | | | OFF | | | | | | | |
| ★ Disable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | ON | | | | | | |
| ★ Enable Bill Reject 4 Times BA Stop By 30 Sec | | | | | | OFF | | | | | | |
| ★ Harness Disable | | | | | | | ON | | | | | |
| ★ Harness Enable | | | | | | | OFF | | | | | |
| ★ Inhibit Active HIGH | | | | | | | | ON | | | | |
| ★ Inhibit Active LOW | | | | | | | | OFF | | | | |
| ★ Power On Stacker | | | | | | | | | ON | | | |
| ★ Power On Reject | | | | | | | | | OFF | | | |
| ★ Slow Output Pulse | Lo 50 ms | | | | | | | | | ON | | |
| | Hi 300 ms | | | | | | | | | | | |
| ★ Fast Output Pulse | Lo 50 ms | | | | | | | | | OFF | | |
| | Hi 100 ms | | | | | | | | | | | |
| ★ Reserved | | | | | | | | | | | ON | |
| ★ Reserved | | | | | | | | | | | OFF | |
| ★ Reserved | | | | | | | | | | | | ON |
| ★ Reserved | | | | | | | | | | | | OFF |

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 AUD5(Pulse/MDB/RS232 106U)

DIP SWITCHES SETTING : 2(Pulse)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal High | ON | | | |
| | Credit-Pulse Normal Low | OFF | | | |
| ★ | Pulse Mode | | ON | | |
| | Other Mode | | OFF | | |
| ★ | 1 pulse / AUD 5 | | | OFF | OFF |
| | 2 pulse / AUD 5 | | | OFF | ON |
| | 4 pulse / AUD 5 | | | ON | OFF |
| | 20 pulse / AUD 5 | | | ON | ON |

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 106U)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|------------|-----|-----|-----|-----|
| ★ | Reserved | ON | | | |
| | Reserved | OFF | | | |
| | Pulse Mode | | ON | | |
| ★ | Other Mode | | OFF | | |
| | MDB | | | OFF | OFF |
| ★ | RS232 106U | | | OFF | ON |
| | Reserved | | | ON | OFF |
| | Reserved | | | ON | ON |

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

| | FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|------------|-----|-----|-----|-----|
| ★ | Reserved | ON | | | |
| | Reserved | OFF | | | |
| | Pulse Mode | | ON | | |
| ★ | Other Mode | | OFF | | |
| ★ | MDB | | | OFF | OFF |
| | RS232 106U | | | OFF | ON |
| | Reserved | | | ON | OFF |
| | Reserved | | | ON | ON |

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2)Please open the panel of front, and can see the DIP switch.

Currency Assign Data

| Interface Bill value | Pulse | MDB | RS232 106U |
|-------------------------|---------|---------|------------|
| BV1 | AUD 5 | AUD 5 | AUD 5 |
| BV2 | AUD 10 | AUD 10 | AUD 10 |
| BV3 | AUD 20 | AUD 20 | AUD 20 |
| BV4 | AUD 50 | AUD 50 | AUD 50 |
| BV5 | AUD 100 | AUD 100 | AUD 100 |