

U72 Option Switch Settings (Pulse/MDB/RS232 106U)

Supported bill VND 10K, 20K, 50K, 100K, 200K, 500K 6 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject VND 10K & 20K	ON											
★ Accept VND 10K & 20K	OFF											
★ Reject VND 50K & 100K		ON										
★ Accept VND 50K & 100K		OFF										
★ Reject VND 200K & 500K			ON									
★ Accept VND 200K & 500K			OFF									
★ High Acceptance				ON								
★ High Security				OFF								
★ Enable, if fishing, BA doesn't work anymore					ON							
★ Disable, if fishing, BA Stop 3 minute.					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active HIGH								ON				
★ Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject									OFF			
★ Slow Output Pulse	Lo 50 ms										ON	
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms										OFF	
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 VND6(Pulse/MDB/RS232 106U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / VND 10K			OFF	OFF
	2 pulse / VND 10K			OFF	ON
	4 pulse / VND 10K			ON	OFF
	20 pulse / VND 10K			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 106U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 106U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 106U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface Bill value	Pulse	MDB	RS232 106U
BV1	VND 10K	VND 10K	VND 10K
BV2	VND 20K	VND 20K	VND 20K
BV3	VND 50K	VND 50K	VND 50K
BV4	VND 100K	VND 100K	VND 100K
BV5	VND 200K	VND 200K	VND 200K
BV6	VND 500K	VND 500K	VND 500K