

U72 Option Switch Settings (Pulse/MDB/RS232 002)

Supported bill TTD 1, 5, 10, 20, 50, 100 6 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TTD 1 & 5	ON											
★ Accept TTD 1 & 5	OFF											
★ Reject TTD 10 & 20		ON										
★ Accept TTD 10 & 20		OFF										
★ Reject TTD 50 & 100			ON									
★ Accept TTD 50 & 100			OFF									
★ High Acceptance				ON								
★ High Security				OFF								
★ Enable, if fishing, BA doesn't work anymore					ON							
★ Disable, if fishing, BA Stop 3 minute.					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active HIGH								ON				
★ Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject									OFF			
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 TTD6(Pulse/MDB/RS232 002)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / TTD 1			OFF	OFF
	2 pulse / TTD 1			OFF	ON
	4 pulse / TTD 1			ON	OFF
	20 pulse / TTD 1			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 002)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 002			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 002			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface Bill value	Pulse	MDB	RS232 002
BV1	TTD 1	TTD 1	TTD 1
BV2	TTD 5	TTD 5	TTD 5
BV3	TTD 10	TTD 10	TTD 10
BV4	TTD 20	TTD 20	TTD 20
BV5	TTD 50	TTD 50	TTD 50
BV6	TTD 100	TTD 100	TTD 100