

U72 Option Switch Settings (Pulse/MDB/RS232 104U)

Supported bill IDR 1000, 2000, 5000, 10000, 20000, 50000, 100000 7 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject IDR 1000	ON											
★ Accept IDR 1000	OFF											
★ Reject IDR 2000		ON										
★ Accept IDR 2000		OFF										
★ Reject IDR 5000			ON									
★ Accept IDR 5000			OFF									
★ Reject IDR 10000				ON								
★ Accept IDR 10000				OFF								
★ Reject IDR 20000					ON							
★ Accept IDR 20000					OFF							
★ Reject IDR 50000						ON						
★ Accept IDR 50000						OFF						
★ Reject IDR 100000							ON					
★ Accept IDR 100000							OFF					
★ Inhibit Active HIGH								ON				
Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject									OFF			
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 IDR7(Pulse/MDB/RS232 104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / IDR 1000			OFF	OFF
	2 pulse / IDR 1000			OFF	ON
	4 pulse / IDR 1000			ON	OFF
	20 pulse / IDR 1000			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2)Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface Bill value	Pulse	MDB	RS232 104U
BV1	IDR 1000	IDR 1000	IDR 1000
BV2	IDR 2000	IDR 2000	IDR 2000
BV3	IDR 5000	IDR 5000	IDR 5000
BV4	IDR 10000	IDR 10000	IDR 10000
BV5	IDR 20000	IDR 20000	IDR 20000
BV6	IDR 50000	IDR 50000	IDR 50000
BV7	IDR 100000	IDR 100000	IDR 100000