

# U72 Option Switch Settings (Pulse/MDB/RS232 104U/MARS)

Supported bill USD 1, 2, 5, 10, 20, 50, 100 7 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject USD 2		ON										
★ Accept USD 2		OFF										
★ Reject USD 5			ON									
★ Accept USD 5			OFF									
★ Reject USD 10				ON								
★ Accept USD 10				OFF								
★ Reject USD 20					ON							
★ Accept USD 20					OFF							
★ Reject USD 50						ON						
★ Accept USD 50						OFF						
★ Reject USD 100							ON					
★ Accept USD 100							OFF					
★ Inhibit Active HIGH								ON				
Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject									OFF			
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

# U72 USD7(Pulse/MDB/RS232 104U)

## DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / USD 1			OFF	OFF
	2 pulse / USD 1			OFF	ON
	4 pulse / USD 1			ON	OFF
	20 pulse / USD 1			ON	ON

★Manufacture setting

## DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 104U			OFF	ON
	Reserved			ON	OFF
	MARS			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2)Please open the panel of front, and can see the DIP switch.

## Currency Assign Data

Interface Bill value	Pulse	MDB	RS232 104U	MARS
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 2	USD 2	USD 2	USD 2
BV3	USD 5	USD 5	USD 5	USD 5
BV4	USD 10	USD 10	USD 10	USD 10
BV5	USD 20	USD 20	USD 20	USD 20
BV6	USD 50	USD 50	USD 50	USD 50
BV7	USD 100	USD 100	USD 100	USD 100

## DIP SWITCHES SETTING : 2(RS232 104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 104U			OFF	ON
	Reserved			ON	OFF
	MARS			ON	ON

★Manufacture setting

## DIP SWITCHES SETTING : 2(MARS)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	RS232 104U			OFF	ON
	Reserved			ON	OFF
★	MARS			ON	ON

★Manufacture setting