

U72 Option Switch Settings (Pulse/MDB/RS232 104U)

Supported bill INR 5, 10, 20, 500, 2000 5 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject INR 5 & 10	ON											
★ Accept INR 5 & 10	OFF											
★ Reject INR 20 & 500		ON										
★ Accept INR 20 & 500		OFF										
★ Reject INR 2000			ON									
★ Accept INR 2000			OFF									
★ High Acceptance				ON								
★ High Security				OFF								
Enable, if fishing, BA doesn't work anymore					ON							
★ Disable, BA works normally					OFF							
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active HIGH								ON				
★ Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject										OFF		
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 INR5(Pulse/MDB/RS232 104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / INR 5			OFF	OFF
	2 pulse / INR 5			OFF	ON
	4 pulse / INR 5			ON	OFF
	20 pulse / INR 5			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(RS232 104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	RS232 104U			OFF	ON
	Reserved			ON	OFF
	Reserved			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2)Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface	Pulse	MDB	RS232 104U
Bill value			
BV1	INR 5	INR 5	INR 5
BV2	INR 10	INR 10	INR 10
BV3	INR 20	INR 20	INR 20
BV4	Reserved	Reserved	Reserved
BV5	Reserved	Reserved	Reserved
BV6	INR 500	INR 500	INR 500
BV7	INR 2000	INR 2000	INR 2000