

U72 Option Switch Settings (MDB)

Supported bill VND 1K, 2K, 5K, 10K, 20K 5 Bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject VND 1K	ON											
★ Accept VND 1K	OFF											
★ Reject VND 2K & 5K		ON										
★ Accept VND 2K & 5K		OFF										
★ Reject VND 10K & 20K			ON									
★ Accept VND 10K & 20K			OFF									
★ High Acceptance				ON								
★ High Security				OFF								
★ Enable, if fishing, BA doesn't work anymore					ON							
★ Disable, if fishing, BA Stop 3 minute.					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active HIGH								ON				
★ Inhibit Active LOW								OFF				
★ Power On Stacker									ON			
★ Power On Reject										OFF		
★ Slow Output Pulse	Lo 50 ms									ON		
	Hi 300 ms											
★ Fast Output Pulse	Lo 50 ms									OFF		
	Hi 100 ms											
★ ScalingFactor & *DecimalPlaces	1000	0									ON	ON
	1000	0									ON	OFF
	1000	1									OFF	ON
	1000	*2									OFF	OFF

★Manufacture setting

Note : Please reset the bill acceptor after any changes on Dip switch.

U72 VND5(MDB)

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	MDB	ON			
	MDB	OFF			
	MDB		ON		
★	MDB		OFF		
★	MDB			OFF	OFF
	MDB			OFF	ON
	MDB			ON	OFF
	MDB			ON	ON

★Manufacture setting

Note :(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Please open the panel of front, and can see the DIP switch.

Currency Assign Data

Interface Bill value	MDB
BV1	VND 1K
BV2	VND 2K
BV3	VND 5K
BV4	VND 10K
BV5	VND 20K