



TP70P3B/P5 Protocol for RS232 002 / Pulse

NIO7 Support bill 10、20、50、100、200、500、1000 (Nicaragua)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NIO 10	OFF	OFF	OFF							
	2 Pulse / NIO 10	OFF	OFF	ON							
	3 Pulse / NIO 10	OFF	ON	OFF							
	4 Pulse / NIO 10	OFF	ON	ON							
	5 Pulse / NIO 10	ON	OFF	OFF							
	10 Pulse / NIO 10	ON	OFF	ON							
	20 Pulse / NIO 10	ON	ON	OFF							
	100 Pulse / NIO 10	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NIO 10 & 20				ON						
	Reject NIO 10 & 20				OFF						
★	Accept NIO 50				ON						
	Reject NIO 50				OFF						
★	Accept NIO 100				ON						
	Reject NIO 100				OFF						
★	Accept NIO 200				ON						
	Reject NIO 200				OFF						
★	Accept NIO 500 & 1000				ON						
	Reject NIO 500 & 1000				OFF						

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Reserved				ON
★	Reserved				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.