



TP70P3B/P5 Protocol for RS232 104U / Pulse

PYG6 Support bill 2000、5000、10000、20000、50000、100000 (Paraguay)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
Normal Pulse	Special Pulse										
★ 1 Pulse / PYG 1000	1 Pulse / PYG 2000	OFF	OFF	OFF							
2 Pulse / PYG 1000	1 Pulse / PYG 5000	OFF	OFF	ON							
3 Pulse / PYG 1000	1 Pulse / PYG 10000	OFF	ON	OFF							
4 Pulse / PYG 1000	1 Pulse / PYG 20000	OFF	ON	ON							
5 Pulse / PYG 1000	1 Pulse / PYG 50000	ON	OFF	OFF							
10 Pulse / PYG 1000	1 Pulse / PYG 100000	ON	OFF	ON							
20 Pulse / PYG 1000	1 Pulse / PYG 500000	ON	ON	OFF							
100 Pulse / PYG 1000	1 Pulse / PYG 1000000	ON	ON	ON							
Fast Output Pulse	Lo=50ms Hi=100ms				ON						
★ Slow Output Pulse	Lo=50ms Hi=300ms				OFF						
Inhibit level Active Low						ON					
★ Inhibit level Active High						OFF					
★ Accept PYG 2000 & 5000							ON				
Reject PYG 2000 & 5000							OFF				
★ Accept PYG 10000								ON			
Reject PYG 10000								OFF			
★ Accept PYG 20000									ON		
Reject PYG 20000									OFF		
★ Accept PYG 50000										ON	
Reject PYG 50000										OFF	
★ Accept PYG 100000											ON
Reject PYG 100000											OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
RS232 Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Special Pulse				ON
★ Normal Pulse				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch