



# TP77P3B/P5 Protocol for RS232 104U / Pulse / ccTalk

THB5 Support bill 20、50、100、500、1000 (Thailand)

## DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF	OFF							
	2 Pulse / THB 10	OFF	OFF	ON							
	3 Pulse / THB 10	OFF	ON	OFF							
	4 Pulse / THB 10	OFF	ON	ON							
	5 Pulse / THB 10	ON	OFF	OFF							
	10 Pulse / THB 10	ON	OFF	ON							
	20 Pulse / THB 10	ON	ON	OFF							
	100 Pulse / THB 10	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept THB 20						ON				
	Reject THB 20						OFF				
★	Accept THB 50							ON			
	Reject THB 50							OFF			
★	Accept THB 100								ON		
	Reject THB 100								OFF		
★	Accept THB 500									ON	
	Reject THB 500									OFF	
★	Accept THB 1000										ON
	Reject THB 1000										OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

## DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol (SW3 OFF SW4 OFF)		ON		
	RS232 Protocol (SW3 OFF SW4 OFF)		OFF		
	ccTalk 8 bit			ON	ON
★	Reserved			OFF	ON
	Reserved			ON	OFF
★	Pulse / RS232			OFF	OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch